TOA A-2060 Mixer Power Amplifier – 60W 100V Line Public Address Amp for Restaurants & Retail Stores



0.00 SAR ✓ In Stock

FEATURES :

High-Quality Sound
Watt: 60W
FREQUENCY: 50 – 20,000 Hz
MIC Port: 03, AUX: 02
Priority Paging

TOA A-2060 60Watt Mixer Power Amplifier

POWER SOURCE	220 V AC, or 24 V DC
RATED OUTPUT	60 W
POWER CONSUMPTION	72 W (EN60065), 4 A (DC operation at rated output)
FREQUENCY RESPONSE	50 – 20,000 Hz (±3 dB)
DISTORTION	1% or less at 1 kHz, 1/3 rated power
INPUT	MIC 1 – 3: -60 dB*, 600 Ω, balanced, equivalent to XLR-3-31 type AUX 1, 2: -20 dB*, 10 kΩ, unbalanced, RCA pin jack Mute: Contact screw terminal (for MIC 1)
OUTPUT	Speaker out: Balanced (floating), M3.5 screw terminal, distance between barriers: 8.3 mm (0.33″) High impedance: 170 Ω (100 V), 83 Ω (70 V) Low impedance: 4 Ω (15.5 V) Rec out: 0 dB*, 600 Ω, unbalanced, RCA pin jackTOA A-2060 Mixer Power Amplifier Bangladesh
PHANTOM POWER	DC +21 V (MIC 1)
S/N RATIO	60 dB or more
TONE CONTROL	Bass: ±10 dB at 100 Hz Treble: ±10 dB at 10 kHz
FINISH	Panel: ABS resin, black Case: Steel plate, black
DIMENSIONS	420 (W) × 100.9 (H) × 280.3 (D) mm (16.54″ × 3.97″ × 11.04″)
WEIGHT	7 kg (15.43 lb)