TOA A-3606D Digital Mixer Amplifier | 60W, Emergency Alerts



0.00 SAR ✓ In Stock

FEATURES :

- Power Output: 60W (8Ω), 120W (4Ω)
- Input Channels: 6 Mic/Line Inputs, 2 AUX Inputs
- Total Harmonic Distortion: < 0.1%
- Signal to Noise Ratio: > 80 dB

TOA A-3606D Digital Mixer Amplifier	
Power source	100 - 240 V AC, 50 / 60 Hz
Power / current consumption	40 W (EN62368-1), 96 W (rated output)
Frequency response	50 Hz - 20 kHz
Rated output	60 W
Speaker output	Speaker: low impedance: 8-16 Ω, high impedance: 100 V, direct, zone 1, zone 2.
Control input	4 channels, no-voltage make contact input, open voltage: 35 V DC or less, short-circuit current: 10 mA or less, removable terminal block (3.81 mm, 4 pins)
Control output	Power remote, emergency, zone control: withstand voltage 30 VDC, control current 25 mA or less, removable terminal block
Controls	7x volume for inputs, bass, treble, master volume, zone 1 & 2 switch, power
Connectable microphones	6
Inputs	Input 1+2: -60/-20 dBV, 600 Ω, balanced, phantom power switchable; Inputs 3+4: -60 dBV, 600 Ω, balanced, phantom power switchable; all with removable terminal block; Inputs 5+6: -60 dBV, 600 Ω, balanced, removable terminal block / -20 dBV, 10 kΩ, unbalanced, RCA jacks, selectanble; Input 7: -20 dBV, 10 kΩ, unbalanced, 2 RCA jacks. Power amplifier input 0 dBV, 600 Ω, unbalanced, RCA jack
Dimensions	420 x 96.1 x 313.1 mm (W x H x D)
Operating temperature	- 10 °C to + 40 °C (14 °F to 104 °F)