



0.00 SAR ✓ In Stock

FEATURES :

- **Model: A-3624D**
- Power Source: 100 -240V
- Rated Output: 240 W
- S/N Ratio: 88 dB
- Weight: 5 kg

+966 530651576 | www.unityservicesksa.com

Toa A-3624D Digital Mixer Amplifier

Power Source	100 - 240 V AC, 50/60Hz
Rated Output	240 W
Power/Current Consumption	314 W (Rated output), 70 W (based on EN62368), 200 mA or less (when power switch is OFF)
Frequency Response	50 Hz - 20 kHz ± 3 dB (1/8 rated output)
Distortion	1 % or less at 1 kHz, rated power (20 kHz LPF (AUX-0025))
Tone Control	Bass: ± 10 dB at 100 Hz Treble: ± 10 dB at 10 kHz
S/N Ratio	88 dB or more (Master volume: min.) 76 dB or more (Master volume: max.) 55 dB or more (INPUT 1 - 6) 72 dB or more (INPUT 7) (A-weighted)
Audio Input	INPUT 1, 2: -60 dB(*1)(MIC) / -20 dB (*1) (LINE) selectable, 600 Ω , electronically-balanced, removable terminal block (3 pins) Note: MIC inputs are equipped with phantom power (24V DC, ON/OFF switchable) INPUT 3, 4: -60 dB(*1), 600 Ω , electronically-balanced, removable terminal block (3 pins) Note: MIC inputs are equipped with phantom power (24V DC, ON/OFF switchable) INPUT 5, 6: MIC (BUS 1) / LINE (BUS 2) selectable MIC : -60 dB(*1), 600 Ω , electronically-balanced, removable terminal block (3 pins) LINE: -20 dB (*1), 10 k Ω , unbalanced, RCA pin jack x 2 INPUT 7: -20 dB(*1), 10 k Ω , unbalanced, RCA pin jack x 2 PWR AMP IN: 0 dB (*1), 600 Ω , unbalanced, RCA pin jack
Input Bus	INPUT 1 - 4: BUS 1 INPUT 5 - 6: BUS 1/BUS 2 selectable INPUT 7: BUS 2
Audio Output	Speaker out: Low impedance (4 - 16 Ω) / High impedance (DIRECT, ZONE 1, ZONE 2: 100 V / total 42 Ω), removable terminal block (6 pins) (ZONE 1 / ZONE 2 is selectable, max. 240 W per output) Rec out: 0 dB(*1), 600 Ω , unbalanced, RCA pin jack Line out 1, 2: 0 dB (*1) , 600 Ω , unbalanced, RCA pin jack (Interlock with zone selection is possible)
Operating Temperature	-10°C to +40°C
Operating Humidity	85 %RH or less (no condensation)
Dimensions	420 (W) $\times$ 96.1 (H) $\times$ 313.1 (D) mm
Weight	5 kg