



0.00 SAR ✓ In Stock

FEATURES :

- 240 W rated output
- User-friendly front panel
- Excellent frequency response
- 100 V / 70 V line
- 3 MIC inputs, 2 AUX inputs

TOA A-2240 240W Mixer amplifier

POWER SOURCE	110 - 120 V AC, or 24 - 30 V DC
RATED OUTPUT	240 W
POWER CONSUMPTION	238 W (EN60065), 520 W (AC operation at rated output), 15 A (DC operation at rated output) TOA A-2240 Mixer Power Amplifier Bangladesh
FREQUENCY RESPONSE	50 - 20,000 Hz (± 3 dB)
DISTORTION	Under 1% at 1 kHz, 1/3 rated power
INPUT	MIC 1 - 3: -60 dB*, 600 Ω , balanced, phone jack AUX 1,2: -20 dB*, 10 k Ω , unbalanced, RCA pin jack
OUTPUT	Speaker out: Balanced (floating) High impedance: 42 Ω (100 V), 21 Ω (70 V) Low impedance: 4 Ω (31 V) Rec out: 0 dB*, 600 Ω , unbalanced, RCA pin jack
PHANTOM POWER	DC +21 V (MIC 1)
S/N RATIO	Over 60 dB
TONE CONTROL	Bass: ± 10 dB at 100 Hz Treble: ± 10 dB at 10 kHz
DIMENSIONS	420 (W) $\times$ 100.9 (H) $\times$ 360.3 (D) mm (16.54" $\times$ 3.97" $\times$ 14.19")
WEIGHT	13.2 kg (29.1 lb) TOA A-2240 Mixer Power Amplifier