



2,200.00 SAR ✓ In Stock

FEATURES :

A-3212DM is a high-performance yet cost-effective mixer power amplifier equipped with MP3 and Bluetooth function. Ideal for broadcasting, paging, or background music in schools, offices, shops, houses of worship and large ballrooms.

+966 530651576 | www.unityservicesksa.com

Toa A-3212DM Digital Mixer Amplifier

Power Source	100 - 240 V AC, 50/60Hz
Rated Output	120 W
Power Consumption	44 W (AC operation at 1/8 maximum output without clip)
Frequency Response	50 - 20,000 Hz
Input	MIC 1: 1 mV (-60 dB*), 600 Ω , balanced, phone jack, selectable to RJ45 MIC 2-3: 1 mV (-60 dB*), 600 Ω , balanced, phone jack MIC 4: 1 mV (-60 dB*) 600 Ω , balanced, phone jack, selectable to AUX 1 AUX 1: 100 mV (-20 dB*), 10 k Ω , unbalanced, RCA pin jack, selectable to MIC 4 AUX 2: 100 mV (-20 dB*), 10 k Ω , unbalanced, RCA pin jack MP3: LED Display, Support USB, SD/MMC card (up to 32GB), Bluetooth, Radio FM, Record
Output	Speaker out: Speaker Output in screw type terminal Direct line (selectable): 83 Ω (100 V) or 4 Ω Rec out: 0 dB*, 600 Ω , unbalanced, RCA pin jack
Phantom Power	DC +21 V (MIC 1)
S/N Ratio	Over 60 dB
Tone Control	Bass: ± 10 dB at 100 Hz Treble: ± 10 dB at 10 kHz
Total Harmonic Distortion	Under 1% at 1 kHz, 1/3 rated power
Finish	Panel: ABS resin, black Case: Steel plate, black
Dimensions	420 (W) $\times$ 100.9 (H) $\times$ 357 (D) mm
Weight	4.6 kg
Accessory	Antenna FM radio (1m) $\times$ 1