



3,400.00 SAR ✓ In Stock

FEATURES :

A-3248D is a high performance yet cost effective mixer power amplifier suited for broadcasting, paging, or background music in schools, offices, shops, houses of worship and large ballrooms.

+966 530651576 | www.unityservicesksa.com

TOA A-3248D Digital Mixer Amplifier

Power Source	100 – 240 V AC, 50/60Hz
Rated Output	480 W
Power Consumption	99 W (AC operation at 1/8 maximum output without clip)
Frequency Response	50 – 20,000 Hz
Input	MIC 1: 1 mV (-60 dB*), 600 Ω, balanced, phone jack, selectable to RJ45 MIC 2-3: 1 mV (-60 dB*), 600 Ω, balanced, phone jack MIC 4: 1 mV (-60 dB*) 600 Ω, balanced, phone jack, selectable to AUX 1 AUX 1: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack, selectable to MIC 4 AUX 2: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack
Output	Speaker out: Speaker Output in screw type terminal Direct line (selectable): 21 Ω (100 V) or 4 Ω Rec out: 0 dB*, 600 Ω, unbalanced, RCA pin jack
Phantom Power	DC +21 V (MIC 1)
S/N Ratio	Over 60 dB
Total Harmonic Distortion	Under 1% at 1 kHz, 1/3 rated power
Tone Control	Bass: ±10 dB at 100 Hz Treble: ±10 dB at 10 kHz
Finish	Panel: ABS resin, black Case: Steel plate, black
Dimensions	420 (W) × 100.9 (H) × 357 (D) mm
Weight	5.0 kg