



0.00 SAR ✓ In Stock

FEATURES :

Model: A-3248DME

Power Source: 100 -240V

Rated Output: 480 W

Frequency: 50 - 20,000 Hz

Weight: 5.0 kg

+966 530651576 | www.unityservicesksa.com

TOA A-3248DME 480W Digital Mixer Amplifier

Power Source	100 - 240 V AC, 50/60Hz
Rated Output	480 W
Power Consumption	99 W (AC operation at 1/8 maximum output without clip)
Frequency Response	50 - 20,000 Hz
Input	MIC 1: 1 mV (-60 dB*), 600 Ω, balanced, phone jack, selectable to RJ45 MIC 2-5: 1 mV (-60 dB*), 600 Ω, balanced, phone jack AUX 1-2: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack MP3: LED Display, Support USB, SD/MMC card (up to 32GB), Bluetooth, Radio FM, Record
Output	Speaker out: Speaker Output in screw type terminal Direct line (selectable): 21 Ω (100 V) or 4 Ω Rec out: 0 dB*, 600 Ω, unbalanced, RCA pin jack
Phantom Power	DC +21 V (MIC 1)
S/N Ratio	Over 60 dB
Tone Control	±10 dB at 80 Hz, 315 Hz, 1 kHz, 3.15 kHz, 8 kHz
Dimensions	420 (W) × 100.9 (H) × 357 (D) mm
Weight	5.0 kg