# TOA A-3248DMZ Digital Mixer Amplifier with MP3




**3,850.00 SAR** ✓ In Stock

**FEATURES :**

- Digital Mixer Amplifier
- Power Source: 100 – 240 V AC
- Rated Output: 480 Watt
- S/N Ratio: Over 60 dB
- Max Input Mic 04, Aux 02

## TOA A-3248DMZ Digital Mixer Amplifier

| | |
|---|---|
| POWER SOURCE | 100 – 240 V AC, 50/60Hz |
| RATED OUTPUT | 480 W |
| POWER CONSUMPTION | 99 W (AC operation at 1/8 maximum output without clip) |
| FREQUENCY RESPONSE | 50 – 20,000 Hz |
| INPUT | MIC 1: 1 mV (-60 dB*), 600 Ω, balanced, phone jack, selectable to RJ45 MIC 2-3: 1 mV (-60 dB*), 600 Ω, balanced, phone jack MIC 4: 1 mV (-60 dB*) 600 Ω, balanced, phone jack, selectable to AUX 1 AUX 1: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack, selectable to MIC 4 AUX 2: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack MP3: LED Display, Support USB, SD/MMC card (up to 32GB), Bluetooth, Radio FM, Record |
| OUTPUT | Speaker out: Speaker Output in screw type terminal Direct line (selectable): 21 Ω (100 V) or 4 Ω Rec out: 0 dB*, 600 Ω, unbalanced, RCA pin jack 5-zone selector (all zones simultaneously selectable) |
| PHANTOM POWER | DC +21 V (MIC 1) |
| TOTAL HARMONIC DISTORTION | Under 1% at 1 kHz, 1/3 rated power |
| TONE CONTROL | Bass: ±10 dB at 100 Hz Treble: ±10 dB at 10 kHz |
| DIMENSIONS | 420 (W) × 100.9 (H) × 357 (D) mm |
| WEIGHT | 5.0 kg |