



0.00 SAR ✓ In Stock

FEATURES

The FV-208EV Emergency Message Panel is the emergency broadcast operating section of the EV-200 Series Emergency Public Address System. It need not be installed when the system is used solely for general broadcasting purposes. It has facilities to manually start and reset emergency broadcasts. A total of 8 Emergency messages are recorded in English (default settings), which can be changed by USB data transfer operations from rear panel.

+966 530651576 | www.unityservicesksa.com

TOA FV-208EV Emergency Message Panel

Model	FV-208EV
Power Source	24 V DC (operating range: 19.5 N 27 V) M3 Screw terminal Usable power supply unit: FV-200PS-AS
Power Consumption	200 mA (rated) 100 mA (standby)
Audio Input	Fireman's microphone (accessory) : -55 dB* 2.2 kΩ, unbalanced, XLR connector SO/MMC card slot (up to 32 GB, Type file: MP3 File)
Audio Output	EV Output : -20 dB*, unbalanced, Removable terminal block
Control Input	FA Input, Stop, 8 Messages contact input: No-voltage make contact input, open voltage: 24 V DC, Short circuit current: Under 5 mA, Removable terminal block
Control Output	EV Output : Contact switch (normally open), Removable terminal block 8 Control outputs : Relay contact output, rated voltage: 24 V DC
Frequency Response	20 - 20,000 Hz, ±3 dB
Distortion	Under 1% (1 kHz, Rated output)
Indicator	Power, Fire, Alert, Evacuation, False, Safe Stay, Emer.Stby, PA Test, FA Test, Siren
Operating Temperature	0 °c to +40 °c
Operating Humidity	Under 90% RH (no condensation)
Dimensions	482 (W) x 100 (H) x 281 (D) mm
Weight	2.3 kg (with microphone)
Accessories	Removable terminal plug (4 pins) x4 Removable terminal plug (8 pins) x4, Fireman's microphone x1