Toa P-3248D Digital Booster Amplifier High Quality



0.00 SAR ✓ In Stock

FEATURES :

- Model: P-3248D
- Power Source: 480 W
- Frequency: 50- 20,000 Hz
- S/N Ratio: Over 70 dB
- Weight: 5.2 kg

Toa P-3248D Digital Booster Amplifier High Quality

Power Source	100 - 240 V AC, 50/60Hz or 24 V DC
Rated Output	480 W
Power Consumption	99 W (AC operation at 1/8 maximum output without clip)
Frequency Response	50 - 20,000 Hz
Input	Line In: 0 dB*, 10 kΩ, balanced, screw terminal 100 V Line In: 40 dB*, 30 kΩ, unbalanced, screw terminal
Output	Speaker out: Speaker Output in screw type terminal Direct line (selectable): 21 Ω (100 V) or 4 Ω Rec out: 0 dB*, 600 Ω, unbalanced, screw terminal
S/N Ratio	Over 70 dB
Total Harmonic Distortion	Under 1% at 1 kHz, 1/3 rated power
Tone Control	Bass: ±10 dB at 100 Hz Treble: ±10 dB at 10 kHz
Dimensions	420 (W) × 100.9 (H) × 351.3 (D) mm
Weight	5.2 kg