



0.00 SAR ✓ In Stock

FEATURES :

The P-3548D Power Amplifier delivers 480 W power output. It is so designed that it's power ON/OFF can be remotely controlled when used in conjunction with A-3500/A-3500 Series mixer amplifier (option). The P-3548D can also be used as a stand-alone amplifier. It employs a PFC circuit.

+966 530651576 | www.unityservicesksa.com

TOA P-3548D 480 Watt Digital Amplifier

Power Source	220 - 240 V AC, 50/60Hz
Rated Output	480 W
Power/Current Consumption	601 W (Rated output), 113 W (based on EN62368), 200 mA or less (when power switch is OFF)
Frequency Response	50 Hz - 20 kHz ± 3 dB (1/8 rated output)
Distortion	1 % or less at 1 kHz, rated power (20 kHz LPF (AUX-0025))
S/N Ratio	88 dB or more (Master volume: min.) 76 dB or more (Master volume: max.) (A-weighted)
Audio Input	LINE IN: 0 dB(*1) / -20 dB (*1) (switchable), 600 Ω , transformer balanced, RCA pin jack x 2 SPEAKER LINE IN: 40 dB (*1) (100 V Line), 65 k Ω , transformer balanced, removable terminal block (3 pins)
Audio Output	Speaker out: Low impedance (4 - 16 Ω) / High impedance (21 Ω), removable terminal block (3 pins) LINE OUT: 0 dB (*1) , 600 Ω , unbalanced, RCA pin jack X 2
Control Input	POWER REMOTE IN: No-voltage make contact input, open voltage: 35 V DC or less, Short circuit current: 10 mA or less, removable terminal block (4 pins) EMERGENCY IN: No-voltage make contact input, open voltage: 35 V DC or less, short-circuit current: 10 mA or less, removable terminal block (4 pins)
Control Output	POWER REMOTE OUT: Open collector output, withstand voltage: 30 V DC or less, control current: 25 mA or less, removable terminal block (4 pins) EMERGENCY OUT: Open collector output, withstand voltage 30 V DC or less, control current: 25 mA or less, removable terminal block (4 pins)
Operating Temperature	-10°C to +40°C
Operating Humidity	85 %RH or less (no condensation)
Dimensions	420 (W) $\times$ 96.1 (H) $\times$ 313.1 (D) mm
Weight	5 kg

Accessory

Power Cord (2 m) x 1, Audio Input Removavble Terminal Plug (5 mm, 2 pins) x 1, Control I/O Removable Terminal Plug (3.5 mm, 4 pins) x 2, Speaker Out Removable Terminal Plug (5 mm, 3 pins) x 1, Volume Control Cover x 1