TOA CA-130 Car Amplifier – 30W (60W Max) 12V DC Mobile PA Amplifier for Advertising Vans & Security



0.00 SAR ✓ In Stock

FEATURES :

AUX input for CD player, radio, etc.
Unidirectional dynamic microphone with talk switch
Front pause function
DIN size, easy in-dash installation
Rugged construction

TOA CA-130 Car Amplifier	
POWER SOURCE	Standard voltage: 14 V DC Usable voltage: 10 – 16 V DC (12 V battery used)
POWER CONSUMPTION	5 A or less at rated output
RATED OUTPUT	30 W
OUTPUT IMPEDANCE	4 Ω (BRN), 8 Ω (ORG), Common (WHT) Changeable by changing lead wire connections
DISTORTION	Less than 5% (at 1,000 Hz rated output)
FREQUENCY RESPONSE	100 – 10,000 Hz
INPUT	Mic1, 2: 600 Ω, 4 mV, phone jack Aux : 10 kΩ, 500 mV, phone jack
FINISH	Front panel: ABS resin, black Case : Zinc plated steel sheet
DIMENSIONS	178 (W) × 50 (H) × 144 (D) mm (Mounting device excluded)
WEIGHT	1.1 kg
ACCESSORY	Microphone holder ..... 1, Mounting bracket ..... 1, Mounting screw ..... 1set, Fuse (8 A) ..... 1, Connection cord 1set
ACCESSORY MICROPHONE	Unidirectional dynamic type with talk switch Impedance: 600 Ω Sensitivity : -53 dB (1 kHz, 0 dB = 1 V/Pa)