Bosch PRA-AD608 600W IP Amplifier - 8 Independent 100V Channels



0.00 SAR ✓ In Stock

FEATURES :

- Flexible power partitioning across all channels
- Low power consumption and heat loss
- Full supervision with integrated fail-safe redundancy
- Digital signal processing per channel
- IP-networked on OMNEO for audio and control

Bosch PRA-AD608 600W IP Amplifier	
Dimensions (H x W x D) (mm)	44 x 483 x 400 mm
Frequency response (-3 dB) (Hz)	20 – 20000 Hz
Maximum output power (W)	600 W
Minimum signal-to-noise ratio (dBA)	107 dBA
Operating temperature (°C)	-5 – 50 °C
Operating voltage (VDC)	44 – 60 VDC
Protocols / standards	OMNEO; AES70
Sample rate (kHz)	48 kHz
Weight (kg)	8.80 kg