# Toa A-2030D Digital PA Amplifier Good Quality




**0.00 SAR** ✓ In Stock

**FEATURES :**

- Digital Amplifier
- Watt: 30W
- MIC 1 phantom power
- MIC Port: 03, AUX: 02
- Origin: Japan

## Toa A-2030D Digital PA Amplifier Good Quality

| | |
|---|---|
| Power Source | 220 – 240 V, 50/60Hz |
| Rated Output | 30 W |
| Power Consumption | 12 W (AC operation at 1/8 maximum output without clip) |
| Frequency Response | 50 – 20,000 Hz |
| Distortion Under | 1% at 1 kHz, 1/3 rated power |
| Input | MIC 1-3: -60 dB*, 600 Ω, balanced, phone jack AUX 1, 2: -20 dB*, 10 kΩ, unbalanced, RCA pin jack |
| Output | Speaker out: Balanced (floating) High impedance: 330 Ω (100 V) Rec out: 0 dB*, 600 Ω, unbalanced, RCA pin jack |
| Phantom Power | DC +21 V (MIC 1) |
| S/N Ratio | Over 60 dB |
| Tone Control | Bass: ±10 dB at 100 Hz Treble: ±10 dB at 10 kHz |
| Dimensions | 420 (W) × 100.6 (H) × 280.3 (D) mm (16.54″ × 3.96″ × 11.04″) |
| Weight | 4.0 kg (8.88 lb) |