



620.00 SAR ✓ In Stock

FEATURES :

- High-Quality Sound
- Watt: 30W
- FREQUENCY: 50 – 20,000 Hz
- MIC Port: 02, AUX: 02
- Origin: Japan

+966 530651576 | www.unityservicesksa.com

TOA A-230 Mixer 30 Watt Power Amplifier

POWER SOURCE	240 V AC, 50 Hz
RATED OUTPUT	30 W
POWER CONSUMPTION	34 W (AC operation at EN60065)
FREQUENCY RESPONSE	50 Hz – 20 kHz
DISTORTION	1 % or less at 1 kHz, 1/3 rated power
INPUT	MIC 1: -60 dB* (1.0 mV), 600 Ω, Unbalanced, Equivalent to 5-pin DIN Type MIC 2: -60 dB* (1.0 mV), 600 Ω, Unbalanced, Equivalent to phone jack Type AUX 1, 2: -20 dB* (100 mV), 10 kΩ, unbalanced, RCA pin jack
OUTPUT	Speaker out: Floating balanced High impedance: 330 Ω (100 V) Low impedance: 4 Ω (11 V)
SIGNAL TO NOISE RATIO	60 dB or more (MIC 1, 2) 70 dB or more (AUX 1, 2)
TONE CONTROL	Bass: -10 dB at 100 Hz Treble: -10 dB at 10 kHz
MUTING	MIC 1 overrides other Mic input and AUX inputs with 0 – 30 dB attenuation, attenuation by switch
INDICATOR	Power LED, Signal LED
OPERATING TEMPERATURE	-10 °C to +40 °C (14 °F to 104 °F)
FINISH	Panel: ABS resin, black Hairline Case: Steel plate, black, paint
DIMENSIONS	350 (W) × 105 (H) × 240 (D) mm (13.78" × 4.13" × 9.45")
WEIGHT	3.5 kg (7.72 lb)