TOA A-3224D 240W Digital Mixer Power Amplifier - Professional Public Address Solution



0.00 SAR ✓ In Stock

FEATURES :

Model: A-3224D
Power Source: 100 - 240V
Rated Output: 240 W
Frequency: 50 - 20,000 Hz
Weight: 4.9 kg

TOA A-3224D 240W Digital Mixer Power Amplifier

Power Source	100 - 240 V AC, 50/60Hz
Rated Output	240 W
Power Consumption	62 W (AC operation at 1/8 maximum output without clip)
Frequency Response	50 - 20,000 Hz
Input	MIC 1: 1 mV (-60 dB*), 600 Ω, balanced, phone jack, selectable to RJ45 MIC 2-3: 1 mV (-60 dB*), 600 Ω, balanced, phone jack MIC 4: 1 mV (-60 dB*) 600 Ω, balanced, phone jack, selectable to AUX 1 AUX 1: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack, selectable to MIC 4 AUX 2: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack
Output	Speaker out: Speaker Output in screw type terminal Direct line (selectable): 42 Ω (100 V) or 4 Ω Rec out: 0 dB*, 600 Ω, unbalanced, RCA pin jack
Phantom Power	DC +21 V (MIC 1)
S/N Ratio	Over 60 dB
Tone Control	Bass: ±10 dB at 100 Hz Treble: ±10 dB at 10 kHz
Dimensions	420 (W) × 100.9 (H) × 357 (D) mm
Weight	4.9 kg