TOA A-3248DM 480W Digital Power Amplifier - Integrated USB/Bluetooth Player for Factories, Malls, and Large Venues



0.00 SAR ✓ In Stock

FEATURES :

A 3248DM is a high performance yet cost effective mixer power amplifier equipped with MP3 and Bluetooth function. Ideal for broadcasting, paging, or background music in schools, offices, shops, houses of worship and large ballrooms.

TOA A-3248DM 480W Digital Power Amplifier

Power Source	100 – 240 V AC, 50/60Hz
Rated Output	480 W
Power Consumption	99 W (AC operation at 1/8 maximum output without clip)
Frequency Response	50 – 20,000 Hz
Input	MIC 1: 1 mV (-60 dB*), 600 Ω, balanced, phone jack, selectable to RJ45 MIC 2-3: 1 mV (-60 dB*), 600 Ω, balanced, phone jack MIC 4: 1 mV (-60 dB*) 600 Ω, balanced, phone jack, selectable to AUX 1 AUX 1: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack, selectable to MIC 4 AUX 2: 100 mV (-20 dB*), 10 kΩ, unbalanced, RCA pin jack MP3: LED Display, Support USB, SD/MMC card (up to 32GB), Bluetooth, Radio FM, Record
Output	Speaker out: Speaker Output in screw type terminal Direct line (selectable): 21 Ω (100 V) or 4 Ω Rec out: 0 dB*, 600 Ω, unbalanced, RCA pin jack
Phantom Power	DC +21 V (MIC 1)
S/N Ratio	Over 60 dB
Tone Control	Bass: ±10 dB at 100 Hz Treble: ±10 dB at 10 kHz
Muting	MIC 1: Mutes other input signals by 0-30 dB attenuation
Dimensions	420 (W) × 100.9 (H) × 357 (D) mm
Weight	5.0 kg