TOA AN-9001 Ambient Noise Sensing Microphone – Ceiling Mount Sensor



0.00 SAR ✓ In Stock

FEATURES :

The AN-9001 is an electret condenser microphone designed for ambient noise detection. It is used in conjunction with the AN-001T Ambient Noise Sensor Input module in the 9000 Series system. It can be mounted in a 1-gang electrical box in the ceiling or wall.

TOA AN-9001 Ambient Noise Sensing Microphone – Ceiling Mount Sensor

Phantom Power	14 - 26 V DC
Current Consumption	7 mA (at 24 V DC)
Impedance	200 Ω
Rated Sensitivity	-5 dB (1 kHz, 0 dB = 1 V/Pa)
Frequency Response	100 Hz - 10 kHz
Operating Temperature	-10℃ to +40℃
Finish	Panel: ABS resin, white Frame, Case: Surface-treated steel plate
Dimensions	φ130 × 37 (D) mm
Weight	200 g