TOA D-001R Dual Line Input Module with DSP – 2-Channel RCA Expansion for Digital Mixer Mainframes



0.00 SAR ✓ In Stock

FEATURES :

The D-001R is a line input plug-in module designed for use with the 9000 Series amplifiers. It has 2 channel unbalanced inputs of RCA jacks. Input signals to both channels are mixed together. The D-001R can process effect for TONE/EQ/COMPRESSOR to two inputs independently.

Specification

Power Source	+24 V DC, -24 V DC, +6 V DC
Current Consumption	20 mA (at +24 V DC), 20 mA (at -24 V DC), 75 mA (at +6 V DC)
Input	2 channels, 2RCA/ch mixed, 10 kΩ, unbalanced, RCA pin jack
Input Sensitivity	-60, -54, -48, -42, -36, -30, -24, -18, -10 dB* (selectable)
Frequency Response	20 Hz - 20 kHz, +1, -3 dB
S/N Ratio	70 dB or more (at 20 Hz - 20 kHz BPF, Input short, Input sensitivity: -10 dB)
Sampling Frequency	48 kHz
Tone Control	Bass: ±12 dB (at 100 Hz) Treble: ±12 dB (at 10 kHz)
Parametric Equalizer	10 bands, Frequency: 20 Hz - 20 kHz, 31 points, Variable range: ±12 dB, Q: 0.3 - 5
Compressor	Depth: 1 - 5
Operating Temperature	-10 ℃ to +40 ℃
Dimensions	35 (W) × 78 (H) × 91.5 (D) mm
Weight	95 g