TOA FV-248PA 480W Power Amplifier – 100V Line High-Output Amp



0.00 SAR ✓ In Stock

FEATURES :

Model : FV-248PA
Frequency : 80 Hz - 15 kHz, ±3 dB, 1 kHz
Dimensions : 482 (W) × 132 (H) × 333.2 (D) mm
Weight: 18.5 kg
Power Source : AC: 220 - 230 V

TOA FV-248PA 480W Power Amplifier	
Power Source	AC: 220 - 230 V AC, 50/60 Hz DC: 24 V DC (operating range: 19.5 - 27 V) M4 screw terminal, distance between barriers: 12mm
Power Consumption	AC at rated output: 1110 W (condition: AC230V) AC at no signal: 44 W IEC60065: 480 W
Current Consumption	DC at rated output: 30 A (condition: DC27V) DC at no signal: 1.0 A IEC60065: 10.9 A
Input	2 inputs, 0 dB*, 20 kΩ, balanced, removable terminal plug (3 pins) Input module VP-200VX (Option)
Output Impedance	10 Ω (70 V), 21 Ω (100 V)
Control Output	Fault ouput : Make : Normal, Break : Error or Power Off
S/N Ratio	Over 60 dB
Total Harmonic Distortion	Under 1% (1 kHz, 1/3 rated output)
Frequency Response	80 Hz - 15 kHz, ±3 dB, 1 kHz
LED Indicator	Power (Green), Signal (Green), Peak (Red), Fault (Red) (Light: Overheat)
Operating Temperature	0 ℃ to +40 ℃
Dimensions	482 (W) × 132 (H) × 333.2 (D) mm
Weight	18.5 kg
Accessory	Removable terminal plug (3 pins) x 3, Instruction manual x 1